

5 é / Desp

RK Ô Â ... v 8 â ' k V ° SOD-123FL / xož

Schottky Barrier Rectifiers,SOD-123FL thin package.


□^a / Feats

z ô k ä | ä k ä v k 3 g 9 ' z k ~ ... ä k 9 z 9 k ä È " J ~ ož —) í D } ož


Low power loss, high efficiency.High current capability,low forward voltage drop,High surge capability,
 For use in low voltage, high frequency inverters.Halogen free product.

Đ ÷ / Apab%² " (ož

General purpose.

Ä w] Ô · / EigtCctu**• Ô - æ / Pig**

PIN	DESCRIPTION
1	Cathode
2	Anode

**, M V / Malg**• - ~^a ¢ ož See Marking Instructions.

1N5817W1N5819W

Rev.E Mar.-2019


@ f Parameter	... Z Symbol	f > Rating			% y Unit
		1N5817W	1N5818W	1N5819W	
Maximum Repetitive Peak Reverse Voltage	V_{RRM}	20	30	40	V
Maximum RMS voltage	V_{RMS}	14	21	28	V
Maximum DC Blocking Voltage	V_{DC}	20	30	40	V
Maximum Average Forward Rectified Current	I_{FAVA}	1.0			A
Peak Forward Surge Current, 8.3ms Single Half Sine-wave Superimposed On Rated Load (JEDEC method)	I_{FSM}	25			A

1N5817W1N5819W
Rev.E Mar.-2019

Ô ? d • Ž ¢

Ø □ =) ⌀ / Packg Dim


SOD-123FL





, My f / Ma 11

Marking



1N5817W1N5819W


Rev.E Mar.-2019



蓝箭电子
BLUE ROCKET ELECTRONICS

DATA SHEET

, My f / Ma



a ¢ y

' y ° Z W A

**** y ÿ D Z A Ç A k † v ã W A k e µ ¢ ã 4 Z W A

Note:

' y Product Type Code

**** y Lot No. Code k The 1st "*" means:YM Code k The last 3 "*" means:little Lot
No Code

